USBメモリのVFATフォーマット

USBメモリをVFAT[W95 FAT32 (LBA)]でフォーマットする。

- パーティション タイプの変更
- VFATフォーマット

パーティション タイプの変更

すでにVFATフォーマットのパーティションがあれば不要だがVFATパーティションが無い場合は作成もしくはタイプを変更する。

タイプの変更

fdiskコマンドでパーティションタイプを変更する。

```
$ sudo fdisk /dev/sdb

Command (m for help): t
Selected partition 1
Hex code (type L to list all codes): L

 0  Empty           24  NEC DOS         81  Minix / old Lin bf  Solaris
 1  FAT12           27  Hidden NTFS Win 82  Linux swap / So c1  DRDOS/sec
(FAT-
 2  XENIX root      39  Plan 9          83  Linux           c4  DRDOS/sec
(FAT-
 3  XENIX usr       3c  PartitionMagic  84  OS/2 hidden or  c6  DRDOS/sec
(FAT-
 4  FAT16 <32M      40  Venix 80286     85  Linux extended  c7  Syrinx
 5  Extended        41  PPC PReP Boot   86  NTFS volume set da  Non-FS data
 6  FAT16           42  SFS             87  NTFS volume set db  CP/M / CTOS
/ .
 7  HPFS/NTFS/exFAT 4d  QNX4.x          88  Linux plaintext de  Dell Utility
 8  AIX             4e  QNX4.x 2nd part 8e  Linux LVM       df  BootIt
 9  AIX bootable    4f  QNX4.x 3rd part 93  Amoeba          e1  DOS access
 a  OS/2 Boot Manag 50  OnTrack DM      94  Amoeba BBT      e3  DOS R/O
 b  W95 FAT32       51  OnTrack DM6 Aux 9f  BSD/OS          e4  SpeedStor
 c  W95 FAT32 (LBA) 52  CP/M            a0  IBM Thinkpad hi ea  Rufus
alignment
 e  W95 FAT16 (LBA) 53  OnTrack DM6 Aux a5  FreeBSD         eb  BeOS fs
 f  W95 Ext'd (LBA) 54  OnTrackDM6      a6  OpenBSD         ee  GPT
10  OPUS            55  EZ-Drive        a7  NeXTSTEP        ef  EFI
(FAT-12/16/
11  Hidden FAT12    56  Golden Bow      a8  Darwin UFS      f0  Linux/PA-
RISC b
12  Compaq diagnost 5c  Priam Edisk     a9  NetBSD          f1  SpeedStor
```

```
14  Hidden FAT16 <3 61  SpeedStor       ab  Darwin boot     f4  SpeedStor
16  Hidden FAT16    63  GNU HURD or Sys af  HFS / HFS+      f2  DOS
secondary
17  Hidden HPFS/NTF 64  Novell Netware  b7  BSDI fs         fb  VMware VMFS
18  AST SmartSleep  65  Novell Netware  b8  BSDI swap       fc  VMware
VMKCORE
1b  Hidden W95 FAT3 70  DiskSecure Mult bb  Boot Wizard hid fd  Linux raid
auto
1c  Hidden W95 FAT3 75  PC/IX           bc  Acronis FAT32 L fe  LANstep
1e  Hidden W95 FAT1 80  Old Minix       be  Solaris boot    ff  BBT
Hex code (type L to list all codes): c
Changed type of partition 'Linux' to 'W95 FAT32 (LBA)'.

Command (m for help): p
Disk /dev/sdb: 28.9 GiB, 31037849600 bytes, 60620800 sectors
Disk model: USB Flash Drive
Units: sectors of 1 * 512 = 512 bytes
Sector size (logical/physical): 512 bytes / 512 bytes
I/O size (minimum/optimal): 512 bytes / 512 bytes
Disklabel type: dos
Disk identifier: 0x1e5e705b

Device     Boot Start      End  Sectors  Size Id Type
/dev/sdb1        2048 60620799 60618752 28.9G  c W95 FAT32 (LBA)

Filesystem/RAID signature on partition 1 will be wiped.

Command (m for help): w
The partition table has been altered.
Calling ioctl() to re-read partition table.
Syncing disks.
```

VFATフォーマット

DOS(FAT32)フォーマットを行う。

- -F32: FAT32
- -n: Volume Label

```
$ sudo mkdosfs -F32 -nextdisk /dev/sdb1
```

From:
https://kijima.mydns.jp/dokuwiki/ - **Kijima's private wiki**

Permanent link:
https://kijima.mydns.jp/dokuwiki/doku.php?id=usb%E3%83%A1%E3%83%A2%E3%83%AA%E3%81%AEvfat%E3%83%95%E3%82%A9%E3%83%BC%E3%83%9E%E3%83%83%E3%83%88&rev=1692586504

Last update: **2023/08/21 02:55**